

## **Zinwell ZDX-7000**

### **Before you Start!**

- The below-mentioned procedures must be done using a remote control.
- A valid TENSports RF feed from the antenna must be connected to the IF IN of the Zinwell IRD.
- An authorized smart card (VC) must be inserted in the IRD.
- Connect the video and audio output of the Zinwell IRD to compatible monitoring equipment.

### **Procedures.**

- Press [MENU].

#### In the MAIN MENU

- Using the arrow button [▼][▲]
- Scroll to the “INSTALLATION” option. Indicator button will turn green.
- Press [OK].

#### In the PASSWORD WINDOW

- Key in the PASSWORD = 0000

#### In the INSTALLATION MENU

- Using the arrow button [▼][▲]
- Scroll to the “SEARCH CHANNEL” option. Indicator button turns green.
- Press [OK].

#### In the SEARCH CHANNEL MENU

- Using the arrow button [◀][▶]
- Scroll to “TP” option. Background turns orange.
- Press [OK].
  
- Using the arrow button [◀][▶]
- Scroll to “FREQ” option. Background turns orange.
- Press [OK]. Background turns red.
- Key in the Downlink Frequency = 3716
- Press [OK].
  
- Using the arrow button [◀][▶]
- Scroll to “S/R” option. Background turns orange.
- Press [OK]. Background turns red.
- Key in the Symbol Rate = 20770
- Press [OK].

- Using the arrow button [◀][▶]
- Scroll to “POL” option. Background turns orange.
- Press [OK]. Background turns red.
- Using the arrow button [◀][▶]
- Select the HOR for horizontal option.
- Press [OK].
  
- Using the arrow button [◀][▶]
- Scroll to “NUM” option.
- Press [OK].

The configuration process is completed. Next step is to perform the auto scan.

In the SEARCH CHANNEL MENU

- Press the green button on the remote control. Auto scan will resume automatically.

The tuning process is completed. Select the channel you desire by pressing the channel number.

- 1 → India.
- 2 → Pakistan.
- 3 → Cricket Plus.
- 4 → Middle East.
- 5 → IP5.

You will only receive the channel which your VC is authorized. Turn the volume to maximum.

**HAPPY VIEWING.**